

APPROVED METER SOCKETS

(revised August 2020)



SINGLE PHASE

200 AMP Service - Lever Bypass

Milbank	U4801 or equiv.	OH/UG	
Milbank	U9865-RXL-2-K1-ALT	OH only	
Milbank	U4721-O-BL-ALT	UG only	Preferred

200 AMP Service - Socket/Main - Lever Bypass

Milbank	U5871 or equiv.	OH/UG	Preferred
Milbank	U5872 or equiv.	OH/UG	Preferred
Milbank	U4322-0-5T9 or equiv.	UG	Meter pedestal
Milbank	U6281-XL-200-5T9	OH/UG	Preferred
Milbank	U6012-XL-200-KI-ALT	OH/UG	
Milbank	U5871-XL-200 or 100	OH/UG	

200 AMP Service – 2-Position/Dual Socket - Lever Bypass

Milbank	U2872-XT-5T9	OH/UG	Electrician must provide mechanical lugs (K1350) for line & load side.
---------	--------------	-------	--

320 AMP Service - Lever Bypass

Milbank	U1779-RRL-K3-K2-ALT	OH only	Factory-installed lugs
Milbank	U2448-X-5T9	OH/UG	Electrician must provide mechanical lugs (K1350) for line & (K1350 or K1540) load side.
Milbank	U1797-0-K3L-K2L or equiv.	UG only	Factory-installed lugs.
Milbank	U3000-O-K3L-K2L-ALT	UG	Factory-installed lugs.
Milbank	U1129-O-5T9	UG	Electrician provides lugs.
Milbank	U1079-R-5T9	OH	Electrician provides lugs.
Milbank	U2448-X-5T9	UG	Electrician provides lugs.

COMMERCIAL/RESIDENTIAL METER SOCKETS WITH MAIN – 250 V Max

(120/240V 1 Phase 4-Terminal 320 Amp)

U5059-X-5T9-K3L-ALT		OH/UG	
U5059-X-200-100-K3L-ALT		OH/UG	
U5059-X-200-150-K3L-ALT		OH/UG	
U5059-X-200-200-K3L-ALT		OH/UG	

COMMERCIAL/RESIDENTIAL METER SOCKETS WITH MAIN – 250 V Max

(120/208V 1 Phase 5-Terminal)

U6012-XL-200-5T9		OH/UG	
US871-XL-200-5T9		OH/UG	

400 AMP/800 AMP Service - CT meter package (6-terminal socket)

	Cooperative will provide meter sockets at member's expense.	OH/UG	Electrician must provide CT cabinet, mechanical lugs for line and load side of cabinet.
--	---	-------	---

THREE PHASE

200 AMP Service - Self-Contained - Lever Bypass (7-terminal socket)

Milbank	U4910-O-BL-ALT	UG only	
Milbank	U9701-RXL or equiv.	OH only	Electrician must provide mechanical lugs.
Milbank	U1493-X-ALT	OH/UG	

320 AMP Service - Self-Contained - Lever Bypass (7-terminal socket)

Milbank	U4911-X-QG-BL or equiv.	OH/UG	Electrician must provide mechanical lugs.
---------	-------------------------	-------	---

400 AMP or Larger - 3 PHASE - CT meter package

Cooperative will provide meter sockets at member's expense.

Electrician must provide CT cabinet and mechanical lugs for line & load side of cabinet.