

APPROVED METER SOCKETS

(revised Jan. 2018)



SINGLE PHASE

200 AMP Service - Lever Bypass

| | | | |
|---------|-----------------|-------|--|
| Milbank | U4801 or equiv. | OH/UG | |
|---------|-----------------|-------|--|

200 AMP Service - Socket/Main - Lever Bypass

| | | | |
|---------|-----------------------|-------|----------------|
| Milbank | U5871 or equiv. | OH/UG | Preferred |
| Milbank | U5872 or equiv. | OH/UG | Preferred |
| Milbank | U4322-0-5T9 or equiv. | UG | Meter pedestal |

200 AMP Service – 2-Position/Dual Socket - Lever Bypass

| | | | |
|---------|-----------------|-------|---|
| Milbank | U2872 or equiv. | OH/UG | Electrician must provide mechanical lugs (K1350) for line & load side |
|---------|-----------------|-------|---|

320 AMP Service - Lever Bypass

| | | | |
|---------|-----------------------------|---------|--|
| Milbank | 1797-RXL-K3-K2-1L or equiv. | OH only | Factory-installed lugs |
| Milbank | U2448 or equiv. | OH/UG | Electrician must provide mechanical lugs (K1350) for line & (K1350 or K1540) load side |
| Milbank | U1797-0-K3L-K2L or equiv. | UG only | Factory-installed lugs |

400 AMP/800 AMP Service - CT meter package (6-terminal socket)

| | | | |
|--|---|-------|---|
| | Cooperative will provide meter sockets at member's expense. | OH/UG | Electrician must provide CT cabinet, mechanical lugs for line and load side of cabinet. |
|--|---|-------|---|

THREE PHASE

200 AMP Service - Self-Contained - Lever Bypass (7-terminal socket)

| | | | |
|---------|---------------------|---------|--|
| Milbank | U9701-RXL or equiv. | OH only | Electrician must provide mechanical lugs |
|---------|---------------------|---------|--|

320 AMP Service - Self-Contained - Lever Bypass (7-terminal socket)

| | | | |
|---------|---------------------------|---------|--|
| Milbank | U4911-X-QG-BL or equiv. | OH/UG | Electrician must provide mechanical lugs |
| Milbank | U3000-0-K3L-K2L or equiv. | UG only | Factory-installed lugs |

400 AMP or Larger - 3 PHASE - CT meter package

Meter socket will be provided by Cooperative at member's expense (3 phase only).

Electrician must provide CT cabinet and mechanical lugs for line & load side of cabinet.